

PANTHER RACK 19"

1-10 KVA Ingresso e uscita monofase

MODELLO	PANTHER 1000	PANTHER 3000	PANTHER 6000	PANTHER 10000
Potenza (kVA / W)	1000VA / 900W	3000VA / 2700W	6000VA / 5400W	1000VA / 9000W
INGRESSO / INPUT				
Power Factor	≥ 0.99			
Voltage	1 phase + neutral + ground 200-240 VAC			
Frequency	50Hz / 60Hz +/-5%			
Bypass Voltage	1 phase + neutral + ground 200-240 VAC +/-25%			
Bypass Protection	Short Circuit, Voltage and Frequency Tolerance, Sequence of phases			
USCITA				
Power Factor	0,9			
Voltage	1 phase + neutral + ground 200-230-240 VAC, +/-0,1%			
Frequency	50-60 Hz +/- 1%			
Protections	Overload, Short Circuit, DC balancing, Current Limit			
AC/AC on-line efficiency	> 96%			
Overload	100-125% of the load for 10 min, 125-150% 1 min, >150% trasf bypass			
BATTERIE				
Type of batteries	Maintenance Free, Sealed Lead Acid			
Charging time for 100%	12hr			
Batteries	Internal		External	
Operating Temperature	Ideal 20°C			
Voltage DC	24 VDC	72 VDC	120-276 VDC	
Charging current	30A/250Vdc			
GENERAL				
Display	Display LCD and LED indicators, buzzer			
Batteries Power Supply Alarm	Buzzer every 10 sec			
Low Voltage Alarm	Buzzer every sec			
Overload Alarm	Buzzer every hald sec			
Replacement Batteries Alarm	Buzzer every 2 sec			
Fault Alarm	Buzzer non-stop			
Con o mity	IÒÔÎ2010Ê1Ê2ÈH L ÒPÍ01Î1 L ÒPÍ00J1Ê1Ê2ÈH L ÇÈÙ Î2010Ê1Ê2ÈH			
Measures	F-N Voltage, F-F Current Voltage, Frequency			
LED Indicators	Warning, Bypass, Battery, Inverter			
Operational Temperature	0-40°C			
Protection Degree	IP20			
Humidity Range	< 95% (not condensed)			
Noise level	< 55 Dba			
Net Weight (Kg.)	17	26	23	25
Dim (W x D x H) /mm	440 x 450 x 2U	440 x 520 x 3U	440 x 670 x 3U	440 x 670 x 3U
OPZIONI				
Adaptors	SNMP Network Card			
USB Card	USB Connection			
RS232	RS232 Connection			
Batteries	Different Autonomies, Batterie Ni-CD			
Software	Compatible Software Control with Windows Vista, 7 e 10 / Linux / MAC			

Headquarter - SINERCOM SRL - www.sinercom.it

Via G. Cappalonga, 9A - 00043 Rome Italy - Tel. +39 0679800323 - Fax +39 0679814644

Support Office

Via Cascina Secchi, 285/287 - 24040 ISSO (BG) Italy - Tel. +39 0363 938231 - Fax +39 0363 998235